

ZHEJIANG UNIU-NE Technology CO., LTD 浙江宇力微新能源科技有限公司



U1117 Data Sheet

V 1.1

版权归浙江宇力微新能源科技有限公司

Features

- Maximum output current is 1.1A
- Range of operation input voltage: Max 18V
- Line regulation: 0.03%/V (typ.)

Applications

- I Power Management for Computer Mother Board, Graphic Card
- I LCD Monitor and LCD TV

- Standby current: 1.8mA (typ.)
- Load regulation: 0.2%/A (typ.)
- Environment Temperature: -20°C~85°C
- I DVD Decode Board
- I ADSL Modem
- I Post Regulators For Switching Supplies

General Description

U1117 is a series of low dropout three-terminal regulators with a dropout of 1.3V at 1A load current. U1117 features a very low standby current 1.8mA compared to 5mA of competitor.

Other than a fixed version, Vout = 3.3V, 5.0V, U1117 has an adjustable version, which can provide an output voltage from 3.3 V to 5.0V with only two external resistors.

Typical Application



U1117 offers thermal shut down function, to assure the



Application circuit of U1117 fixed version

Typical Electrical Characteristic





Ordering Information

Marking	Designator	Description		
1117 xx xxxx	1117	Product code		
	XX	Output Voltage 3.3V/5.0V		
	XXXX	LOT		

Note:"XX" stands for output voltages. "XX" stands for LOT.

Typical Application

U1117 has an adjustable version and six fixed versions (3.3V , 5V)

Fixed Output Voltage Version



Application circuit of U1117 fixed version

- 1) Recommend using 10uF tan capacitor as bypass capacitor (C1) for all application circuit.
- 2) Recommend using 10uF tan capacitor to assure circuit stability.

Block Diagram





Absolute Maximum Ratings

Max Input Voltage	
Max Operating Junction Temperature(Tj)150°C	
Ambient Temperature(Ta)40°C~ 85°C	
Storage Temperature(Ts)40°C~150°C	
Lead Temperature & Time	
Courtiery: Exceed these limits to demonst to the device. Expecture to sheel the maximum rating conditions may affect device reliability.	

Caution: Exceed these limits to damage to the device. Exposure to absolute maximum rating conditions may affect device reliability.

Electrical Characteristics

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
Vout	Output voltage	U1117-3.3V 0≤lout≤1A , Vin=5.3V	3.234	3.3	3.366	V
		U1117-5.0V 0≤lout≤1A , Vin=7.0V	4.9	5	5.1	V
∆Vout Line regulation		U1117-3.3V Iout=10mA, 4.8V≤Vin≤12V		0.03	0.2	%/V
		U1117-5.0V lout=10mA, 6.5V≤Vin≤12V		0.03	0.2	%/V
		U1117-3.3 Vin =4.8V, 10mA≤lout≤1A		6	24	mV
		U1117-5.0 Vin =6.5V, 10mA≤lout≤1A		9	36	mV
	Dropout	lout =100mA		1.15	1.3	V
	voltage	lout=1A		1.3	1.5	V
lq	Quiescent Current	U1117-3.3V,Vin=12V		1.8	5	mA
		U1117-5.0V,Vin=12V		1.8	5	mA

TA=25°C , unless otherwise noted.

Note1: All test are conducted under ambient temperature 25°C and within a short period of time 20ms



Detailed Description

U1117 is a series of low dropout voltage, three terminal regulators. Its application circuit is very simple: the fixed version only needs two capacitors and the adjustable version only needs two resistors and two capacitors to work. It is composed of some modules including start-up circuit, bias circuit, bandgap, thermal shutdown, power transistors and its driver circuit and so on.

The thermal shut down modules can assure chip and its application system working safety when the junction temperature is larger than 140°C.

The bandgap module provides stable reference voltage, whose temperature coefficient is compensated by careful design considerations. The temperature coefficient is under 100 ppm/°C. And the accuracy of output voltage is guaranteed by trimming technique.

Typical Performance Characteristics



TA=25 $^{\circ}$ C, unless otherwise noted. Line regulation



Thermal performance with OTP





Package Information

SOT-223



单位:	mm
-----	----

Symbol	Dimension In Millmeter		Symbol	Dimension In Millmeter		
	Min	Max	Symbol	Min	Max	
Α	6.30	6.70	С	-	1.80	
а	2.90	3.10	b	0.91	-	
В	3.30	3.70	с	0.24	0.32	
L	6.70	7.30	C1	0.02	0.10	
a1	0.60	0.80	К	0°	10°	
E1	4.10	5.10				
E	2.00	2.60				

1.版本记录

DATE	REV.	DESCRIPTION
2018/04/ 19	1.0	First Release
2021/12/11	1.1	Layout adjustment

2.免责声明

浙江宇力微新能源科技有限公司保留对本文档的更改和解释权力,不另行通知!客户在下单前应 获取我司最新版本资料,并验证相关信息是否最新和完整。量产方案需使用方自行验证并自担所 有批量风险责任。未经我司授权,该文件不得私自复制和修改。产品不断提升,以追求高品质、 稳定性强、可靠性高、环保、节能、高效为目标,我司将竭诚为客户提供性价比高的系统开发方 案、技术支持等更优秀的服务。

版权所有 浙江宇力微新能源科技有限公司/绍兴宇力半导体有限公司

3.联系我们

浙江宇力微新能源科技有限公司

总部地址: 绍兴市越城区斗门街道袍渎路25号中节能科创园45幢4/5楼

电话: 0575-85087896 (研发部)

传真: 0575-88125157

E-mail: htw@uni-semic.com

无锡地址: 江苏省无锡市锡山区先锋中路6号中国电子(无锡)数字芯城1#综合楼503室 电话: 0510-85297939

E-mail:zh@uni-semic.com

深圳地址:深圳市宝安区西乡街道南昌社区宝源路泳辉国际商务大厦410

电话: 0755-84510976

E-mail:htw@uni-semic.com

